


Commvault Validated Reference Design Specification

Commvault HyperScale™ X Software on SuperMicro 6029P-WTRT



Introduction to Commvault HyperScale X Software

Commvault HyperScale X Software is an intuitive and easy to deploy integrated data protection solution with a distributed scale-out file system that provides unmatched scalability, security, and resilience. Its flexible architecture allows you to get up and running quickly and grow as your needs demand. Commvault Validated Reference Designs accelerate hybrid cloud adoption and deliver:

- Simple, flexible data protection for all workloads including containers, virtual, and databases
- High performance backup and recovery with enhanced recovery capabilities
- Optimized scalability to easily grow capacity in single-node increments as needed, on-prem and in the cloud
- Enhanced resilience with intelligent load balancing of data across disks and nodes and the ability to support concurrent hardware failures
- Built-in ransomware protection via intelligent monitoring to detect data anomalies and alert users

By shifting the secondary storage and data management infrastructure to a scale-out architecture, enterprises can help transform their data centers to be as operationally efficient, resilient and scalable as public cloud infrastructure. Commvault HyperScale X allows organizations to replace limited and legacy backup tools with a modern hybrid cloud-enabled data management solution that eliminates expensive forklift upgrades. The purpose of this technical specification is to provide the complete SuperMicro 6029P-WTRT Commvault Validated Reference Design for Commvault HyperScale X Software.

General availability designation

This configuration is classified as a generally available, meaning it has been tested and validated per the Commvault Validated Reference Design Program. This configuration is subject to change due to updated part numbers or replacement hardware as a result of hardware life cycles. Validated Reference Designs are developed to provide optimized costs, resiliency, and performance. Commvault collaborates with SuperMicro to create fully supported design specifications. Substitutions or modifications to validated design specifications could result in unsupported configurations. Any substitutions or modifications to validated configurations must be approved by both Commvault and SuperMicro. This configuration is currently orderable for customer deployment and supported.

How to use this document

This document details the necessary design components of the Commvault HyperScale X Technology architecture, providing the key components required when purchasing and configuring the infrastructure for a Commvault HyperScale X Software solution. Commvault Reference Designs deliver validated configurations with leading hardware vendor technology complemented by best practices that will accelerate ROI, reduce complexity, and add customer value. The document is broken into a high-level component section detailing the configuration and specific component options that can be selected to satisfy storage capacity and connectivity requirements. This document does not cover overall architecture and design of the Commvault HyperScale X solution, and should be considered as a supplement specific to the SuperMicro server.

SuperMicro 6029P-WTRT Summary

Server overview

Technical specification	
Form factor	2U Rackmount
Motherboard chipset	Intel® C622 chipset
Processors	Intel® Xeon® Silver 4216 – 16 Core CPU
Memory	512GB RAM (8x64GB RDIMM)
Free slots ¹	3x PCIe Slots

Note: Smaller form factor cards can fit in larger form factor slots. However, larger form factor cards cannot fit into smaller form factor slots. For example, an x4 size card can fit in an x8 size slot, however an x8 size card cannot fit in an x4 size slot.

Boot and metadata storage

Boot storage houses the operating system and core Commvault HyperScale X binaries. The metadata storage provides caching areas for such operations as deduplication, indexing, logs and extents. The design specifies dedicated storage for Commvault metadata.

Data storage options

Data storage houses the protected data. Data storage selection dictates the amount of data that each node can accommodate. Initial deployment of Commvault HyperScale X requires a 3-node configuration, each with identical hard disk drive (HDD) capacities. Subsequent expansion of the storage pool can be done by adding individual or multiple nodes. Mixing of different server vendors, models, and/or node capacities within a Storage Pool is supported.

Overall sizing and retention varies per customer and therefore is beyond the scope of this document. Please refer to [Commvault HyperScale Technology sizing documentation](#) to determine the drive size (and node quantity) required for the specific deployment.

Networking options

A minimum of two (2x) 10GB ports are required per node for Commvault HyperScale X installs: one for protected data and one for storage communication between the nodes. It is recommended to have a total of four (4x) ports per node, preferably on two separate cards: two (2x) for data and two (2x) for storage for failover and redundancy. These builds have been designed with this recommendation.

Optional I/O add-on cards

The design includes all core components to support Commvault HyperScale X Technology. Flexibility to accommodate a specific customer use-case comes in the form of number of available PCIe slots in the selected server and is limited to the available options in the "I/O & add-on cards" section below. For example, optional I/O cards for SAS, Ethernet or Fiber Channel connectivity require a free PCIe slot in the server being considered. SAS Connectivity is typically used for direct tape integration, while Fiber Channel (FC) cards are used for Commvault IntelliSnap® technology operations or tape libraries. Additional Ethernet cards may be required for dedicated replication network or to connect to Clients in isolated networks.

¹ These are the slots available in each server for hosting ethernet and fiber-channel (FC) cards. Please ensure any additional cards purchased will physically fit in the server

Bill of Materials

Commvault has partnered with SuperMicro to create SKUs for the validated Commvault Hyperscale X server. There are also component level SKU's for optional Ethernet and Fiber-Channel (FC) connectivity. The number and type of nodes and the specific optional SKUs to be purchased is dependent on the desired backend capacity and connectivity requirements of the customer. The set of SKUs below allow for easy ordering and fulfilment of required hardware without deviating from the tested configuration. Supported components are shown under the heading "I/O & add-on cards". Each server purchase should also include the SKU for hardware service warranty (SMSAD3). Each component listed below has been tested and validated and substitutions cannot be supported. Country-specific components such as power cables are not listed and can be changed as required.

HyperScale X SKU	Description	Usable - capacity/node
SYS-6029P-WTRT-A1-CS071	One Supermicro 6029P-WTRT server, with 2x Intel 4216 CPU's, 512G RAM, 3108 RAID Controller, 2x 480G OS SSD's, 2x 3.8TB NVMe drives. 12x 8TB SAS 12Gb/s HDD. NO Ethernet or FC ports.	~ 50 TiB
SYS-6029P-WTRT-A2-CS071	One Supermicro 6029P-WTRT server, with 2x Intel 4216 CPU's, 512G RAM, 3108 RAID Controller, 2x 480G OS SSD's, 2x 3.8TB NVMe drives. 12x 10TB SAS 12Gb/s HDD. NO Ethernet or FC ports.	~ 63 TiB
SYS-6029P-WTRT-A3-CS071	One Supermicro 6029P-WTRT server, with 2x Intel 4216 CPU's, 512G RAM, 3108 RAID Controller, 2x 480G OS SSD's, 2x 3.8TB NVMe drives. 12x 12TB SAS 12Gb/s HDD. NO Ethernet or FC ports.	~ 75 TiB
SYS-6029P-WTRT-A4-CS071	One Supermicro 6029P-WTRT server, with 2x Intel 4216 CPU's, 512G RAM, 3108 RAID Controller, 2x 480G OS SSD's, 2x 3.8TB NVMe drives. 12x 14TB SAS 12Gb/s HDD. NO Ethernet or FC ports.	~ 88 TiB

I/O & add-on cards: There are three available PCIe slots in each server node. These PCIe slots need to be populated optimally to provide a minimum of 4x 10/25G ethernet ports per server and any other connectivity such as Fiber-Channel (FC) for Intellisnap/ tapeout or additional ethernet for a dedicated replication network. It is therefore important to use the correct (dual or quad-port) ethernet NIC. Network bonding and zoning best-practices recommend the use of ports from separate cards for better resilience. Following are the supported components for this server.

Supermicro SKU	Description
AOC-QLE2742SR	QLE2742-SR 2pts Gen6 32G FC,PCI-E x8 3.0
AOC-S25G-i2S-O	Standard Low profile 2-port 25GbE with SFP28 connectors, based on Intel XXV710 chipset
AOC-STG-I4S	4-port 10GbE Standard LP with SFP+

Ordering examples

Backend capacity	Required connectivity/ node (Ethernet + FC ports)	Required SKU's (ordering)	Comments
125 TiB	Default (4x 10/25G)	3x SYS-6029P-WTRT-A1-CS071 + 6x AOC-S25G-i2S-O + 3x SMSAD3	3x HyperScale X Nodes, each with 12x 8 TB HDD's, 4x 10/25G ethernet ports and support. Usable Capacity = 151 TiB.
325 TiB	Default + 2x FC ports	4x SYS-6029P-WTRT-A4-CS071 + 8x AOC-S25G-i2S-O + 4x AOC-QLE2742SR + 4x SMSAD3	4x HyperScale X Nodes, each with 12x 14 TB HDD's, 4x 10/25G ethernet and 2x FC ports plus support. Usable Capacity = 352 TiB.
425 TiB	Six (6x) Ethernet and 2x FC ports	5x SYS-6029P-WTRT-A4-CS071 + 5x AOC-STG-I4S + 5x AOC-S25G-i2S-O + 5x AOC-QLE2742SR + 5x SMSAD3	5x HyperScale X Nodes, each with 12x 14 TB HDD's, 4x 10G and 2x 10/25G ethernet ports, and 2x FC ports plus support. Usable Capacity = 440 TiB.

Additional resources

Additional information regarding the SuperMicro 6029P-WTRT server can be found on the following website:

<https://www.supermicro.com/en/products/system/2U/6029/SYS-6029P-WTRT.cfm>

Please forward requests for quotes (RFQ) to the mail alias Commvault2SMC@supermicro.com

Commvault HyperScale X Technology integrates with storage arrays, hypervisors, applications and the full range of cloud provider solutions to support the most diverse and dynamic environments. [Learn >](#)